

Series 5 House Service Cutouts

240/415 V

The Series 5 range has been designed as a replacement for existing PILC installations. Interchangeable phase and neutral/earth terminals enable simple installation, without the need to disturb cable polarity. They are equally suited both to paper and polymeric insulated cables.

Sharply serrated bores give complete contact stability with all conductors, copper or aluminium, stranded or solid.

The generously sized sealing chamber makes jointing easier and obviates the need for tight cable bends.

Silver-plated fuse clip contacts wipe silver on first carrier insertion, ensuring reliable long term service.

The range is available in a choice of ratings 60/80A or 100A.

Outgoing cable entries are provided with an auxiliary moulded seal, to accept the sheath as well as the insulation of the cables and are tapered to provide a close fit on the sheathing.

Four incoming cable entries (two at the base and one at each side) are supplied with blanking plugs and two stepped rubber grommets for maximum versatility. Arrangement suits any direction of the existing cable.



- Manufactured from glass reinforced polyester.
- Precise contact pips on fuse-clips together with tightly tolerance phosphor-bronze pressurising springs give consistently low contact resistance – every time.
- Fuse and neutral compartments are interchangeable so that fuse can be orientated on the left or the right side.
- Integral design.

Underground Distribution Fuse Service Equipment


Description	Product Code	
	60/80A	100A
Single Pole and Neutral Cutout*	54181-91	54182-19
Tripe Pole and Neutral Cutout*	54184-01	54182-63

Accessories	Product Code
60/80A Carrier	54365-16
100A Carrier	54365-98
Fuselink to suit 60/80A Carrier. BS HD 60259-3 2010	
16 x 22 x 57mm	16 x 30 x 57mm
30A 58332-04	30A 58332-06
60A 58333-07	60A 58333-11
80A 58334-08	80A 58334-04
100A 58334-09	100A 58334-06


Overall Dimensions (mm)

Model	Length	Width	Depth
SP/N	192	121	98
TP/N	230	217	98

Fuselink Options



Fuselink to BS HD 60259-3 2010' for use with 60A/80A carrier



Fuselink to BS HD 60259-3 2010' for use with 100A carrier

All dimensions in mm



General Note: The equipment in this publication should be installed by a suitably qualified person. Sicame UK Limited reserves the right to make changes in product specification without notice or liability. All information is subject to Sicame UK's own data and is considered accurate at time this document was created.

© 2018 Sicame UK Limited. All rights reserved. No part of this document may be copied or reproduced in whole or in part without prior written approval of Sicame UK Limited.

14688 2014-02-01

